

7664 Keypad Setting

Operation on keypad:

LED

- POWER LED: Flash when battery fault, light off when AC power fault.
 light on when work normal
- Fault LED : light on when system fault
- Arm LED : Light on when system total armed, when part arm slow flash.
 When alarming, quick flash.
- Disarm LED : light on when disarm
- Set : all LED quick flash

Function:

- Stay/arm: If the keypad control many partitions, the password (with authority) +arm key enable arm more than one partitions. That is the control of partitions up to key pads and authority of password.
- Disarm : When keypad control many partitions, the password (with authority)+arm key enable arm more than one partitions simultaneously That is the control of partitions up to keypads and authority of password.
- Partition : when one keypad control more than one partition and user want to operate one partition. User can choose the partition via the partition button The password with authority can arm, disarm or home arm the partition.

Keypad DIP:

There 3 DIP switch on the keypad can achieve 8 different keypad code from 1--8
 Three numbers:123, the "ON" stands dial-up.
 down part with white stands not dial-up, balck stands dial-up already, as picture shows.

Keypad #	DIP switch	zone #
1		41 42 43
2		44 45 46
3		47 48 49
4		50 51 52
5		53 54 55
6		56 57 58
7		59 60 61
8		62 63 64

Note: FC-7664 wont make alarm in 1 minute after power on, it is to avoid false alarm caused by Voltage Instability when power on suddenly after power off. If user arm the system short than 1 minute after power on, panel wont make alarm. We suggest user connect back up battery to the panel.

Zone label:

User can name the zones as follow
 Eg:Name zone #04 as SAFE

[*]+[1234]+[#]+[6]+[OK] AMEND ZONE #:01 +[04]+[OK] ZONE NAME 04:* DEL
Hold***3seconds (01-64) |

→ [7][7][7][7] ZONE NAME 04:* DEL s | + [down arrow] + [2]+ [down arrow] + [3][3][3]+ [down arrow]

→ [3][3] ZONE NAME 04:* DEL SAFE | +[OK]

Note: Press "d" key to move the cursor to the [down arrow] position to be edited.